

SUBSTITUTE SPECIFICATION - MARKED

1

**METHOD, TELECOMMUNICATION SYSTEM AND TELECOMMUNICATION  
HANDSET FOR WIRELESS COMMUNICATION AND TELECOMMUNICATION  
IN A SMART HOME ENVIRONMENT**

**~~FIELD OF TECHNOLOGY~~**

**TECHNICAL FIELD**

The present disclosure is related to smart home networking and communicating over a network using mobile devices.

5

**BACKGROUND**

The term "smart home" refers to the total networking of electronic maintenance systems, communication technology and domestic technology including partial automation in a (family) home or a building (multiple occupancy residence, high-rise building, factory  
10 building, office building, residential block, etc.), in which all the devices and equipment in the residence/building are connected together via a local (internal) network and are also linked to a global (external) network and in which there is increasing integration of the specified networking technologies as a result of general technical convergence.

A key role in this networking principle in the domestic field is certainly played by  
15 wireless communication technology and in particular those technologies that offer simple, fast, user-friendly and not least of all economical solutions to the networking principle. Particular examples of these are all cordless technologies with which the smart home owner can set up their own local network, to have access to the global network, e.g. the internet, in a small radius of up to 300 meters, so-called hotspots, from any current location within said  
20 hotspots. Potential cordless technologies covering the specified short range field preferably include WLAN (Wireless Local Area Network) technology according to the IEEE standard 802.11 (a ... ), DECT (Digital Enhanced Cordless Telecommunication) technology according

SUBSTITUTE SPECIFICATION - MARKED

2

to the ETSI standard ETS 300 175-1...7, Bluetooth technology according to the Bluetooth standard (BT spec. v1.2), WiMax technology according to the IEEE standard 802.16, ZigBee technology according to the IEEE standard 802.15.4 and/or mobile radio technologies in current use, such as the GSM or 3GPP radio system, in conjunction with one of the short-  
5 range radio standards mentioned.

Devices and equipment networked with the wireless communication technology form a telecommunication system in the intelligent home/building, which is able to manage a plurality of functions such as operation and control functions, security and monitoring functions, health and care functions, control functions, logistics functions as well as  
10 communication and maintenance functions.

In such an home/building networked intelligently by means of wireless communication technology, text, audio, video and/or control data is generally transmitted for this purpose between the devices and equipment that are part of the smart home scenario inside (communication) or outside (telecommunication) the networked home/building,  
15 thereby functioning as the data source and/or data sink.

**BRIEF DESCRIPTION**

Accordingly, a method, a telecommunication system and a telecommunication handset is disclosed for wireless communication and telecommunication in a smart home  
20 environment, in which text, audio, video and/or control data is generally transmitted between a data source and a data sink, can be implemented simply and quickly as well as in a user-friendly manner.

Under an exemplary embodiment, a mobile element of a telecommunication system for wireless communication and telecommunication in a smart home environment.  
25 Preferably, the mobile element is configured as a cordless telephone handset or as a mobile telephone, communicating in a network including a base station connected to a circuit-

SUBSTITUTE SPECIFICATION - MARKED

3

switched and/or packet-switched network for ~~holding~~conducting telephone calls and  
sending/receiving text, audio, video and/or control data and at least one mobile element for  
~~holding~~conducting telephone calls and/or sending/receiving text, audio, video and/or control  
data, connected together via an air interface. The mobile element generates control  
5 commands and transmits these in a targeted manner in the course of message traffic between  
the equipment involved in the wireless communication or telecommunication, e.g. embedded  
in HF or radio signals, via the air interface. The control commands are used, among other  
things, to detect text, audio, video and/or control data stored in a data source and to prompt  
and effect the output, release or transfer out of said data to a data sink or its output at the data  
10 source.

On the premise that the mobile element and the equipment mentioned can themselves  
be both data source and data sink, the following exemplary scenario results according to  
which the control commands can be used:

(i) to detect or access text, audio, video and/or control data terminated in the base  
15 station and/or in the mobile element and to transmit this data from the equipment, in which  
the data terminated, to ~~a first~~an INTERNAL data source/data sink with a first mobile  
element assigned to it, ~~a second INTERNAL data source/data sink with a second mobile  
element assigned to it~~ and/or an EXTERNAL data source/data sink connected to the base  
station and assigned to the circuit-switched and/or packet-switched network to output, release  
20 or transfer out said data directly - i.e. without the intermediate connection of a further mobile  
element, the base station and/or other equipment - or indirectly - i.e. for example with the  
intermediate connection of a further mobile element, the base station and/or other equipment;  
and

-(ii) to detect or access text, audio, video and/or control data terminated in the mobile  
25 element, ~~the first INTERNAL data source/data sink~~ and/or the ~~second~~ INTERNAL data  
source/data sink and to transmit this data from the equipment, in which the data terminated,  
via the first mobile element assigned to the ~~first INTERNAL data source/data sink or the  
second mobile element assigned to the second~~ INTERNAL data source/data sink and/or the

SUBSTITUTE SPECIFICATION - MARKED

4

base station to the mobile element, the EXTERNAL data source/data sink, ~~the first~~  
~~INTERNAL data source/data sink and or the second~~and/or the INTERNAL data  
source/data sink to output, release or transfer out said data directly. i.e. for example without  
the intermediate connection of a further mobile element, the base station and/or other  
5 equipment - or indirectly- i.e. for example with the intermediate connection of a further  
mobile element, the base station and/or other equipment.

Under the embodiment, the mobile element generating and transmitting the control  
commands is preferably a cordless telephone handset or mobile telephone with a user-  
friendly operator interface (e.g. keypad, display, menu control, voice control, etc.) with an  
10 additional control functionality designed for the above-mentioned purpose. The cordless  
telephone handset/mobile telephone with this additional functionality can therefore be used as  
a mobile communication instrument as well as a universal controller or remote control  
instrument in the smart home environment, thereby improving the user-friendliness of the  
cordless telephone handset or mobile telephone for the user or operator. The user or operator  
15 only requires a single device for the various smart home scenarios, e.g. telephony, intelligent  
control of devices and equipment in the residential domain (e.g. SOHO: Small  
Office/HOme), and not a number of devices as with the prior art.

In both cases, the cordless telephone handset and the mobile telephone, the base  
station is a preferably cordless base station. The mobile telephone interfaces with this  
20 cordless base station via a cordless interface, e.g. a Bluetooth interface.

Additional advantageous developments of the invention are set out in other exemplary  
embodiments. These include in particular:

A configuration where the control functionality of the mobile element can be  
extended beyond the control commands to check commands which improve user-friendliness  
25 with regard to outputting, releasing or transferring out text, audio, video and/or control data.  
Typical check commands relating to displaying/outputting data are for example the "Forward

SUBSTITUTE SPECIFICATION - MARKED

5

and back", "Terminate", "Interrupt/Pause", "Stop", "Continue", etc. commands and those relating to the release and transfer out are the "Abort", "Delete", "Copy", etc. commands.

To tailor the physical resources for wireless communication and telecommunication in the smart home environment optimally to the data to be transmitted (e.g. voice data and packet data) and the quantity of data generally associated therewith, it is advantageous in some instances to provide different separate air interfaces for the two types of data mentioned. For example, one air interface may be provided for broadband transmission (e.g. Bluetooth interface, IEEE 802.11 a/b/g-based interfaces, etc.) and one air interface may be provided for telephony (e.g. DECT, VVDCT, GSM interface, etc.). For reasons of compatibility, interoperability, and susceptibility to interference, it is sometimes necessary to handle wireless communication and telecommunication in a smart home environment via just one air interface, preferably an air interface that is suitable for broadband transmission (e.g. an interface based on the standard IEEE 802.11 a/b/g). However other cordless interfaces can also be considered, e.g. an interface based on WiMax and/or ZigBee technology.

15

**BRIEF DESCRIPTION OF THE DRAWINGS**

The various objects, advantages and novel features of the present disclosure will be more readily apprehended from the following Detailed Description when read in conjunction with the enclosed drawings, in which:

20 Figure 1 illustrates a first telecommunication system for wireless communication and telecommunication in a smart home environment;

Figure 2 illustrates a second telecommunication system for wireless communication and telecommunication in a smart home environment;

25 Figure 3 illustrates a third telecommunication system for wireless communication and telecommunication in a smart home environment;



SUBSTITUTE SPECIFICATION - MARKED

6

Figure 4 illustrates a first message sequence chart, wherein the user of a mobile element of the telecommunication systems shown in figures 1 to 3 uses the mobile element to wake up a personal computer from standby mode and start it up (first smart home scenario);

5        Figures 5a to 5c illustrate a second message sequence chart, wherein the user of a mobile element of the telecommunication systems shown in figures 1 to 3 uses this to display and process a multimedia message terminated in a base station and to create a new multimedia message (second smart home scenario);

10        Figure 6 illustrates a third message sequence chart, according to which the user of a mobile element of the telecommunication systems shown in figures 1 to 3 uses the mobile element to receive a multimedia message, and to terminate it in the mobile element, and to display it (third smart home scenario);

Figures 7a and 7b illustrate a fourth message sequence chart, according to which the user of a mobile element of the telecommunication systems shown in figures 1 to 3 transmits a multimedia message to another mobile element (fourth smart home scenario);

15        Figures 8a to 8c illustrate a fifth message sequence chart, according to which the user of a mobile element of the telecommunication systems shown in figures 1 to 3 watches a video film that is stored on a personal computer on a television (fifth smart home scenario);

20        Figures 9a to 9c illustrate a sixth message sequence chart, according to which the user of a mobile element of the telecommunication systems shown in figures 1 to 3 outputs an MP3 file that is stored on a personal computer to a HIFI unit (sixth smart home scenario);

Figures 10a to 10c illustrate a seventh message sequence chart, according to which the user of a mobile element of the telecommunication systems shown in figures 1 to 3 is informed by the mobile element of the start of a television program and its interruption by advertisement blocks (seventh smart home scenario); and

SUBSTITUTE SPECIFICATION - MARKED

Figures 11a to 11c illustrate an eighth message sequence chart, according to which the user of a mobile element of the telecommunication systems shown in figures 1 to 3 takes part in televoting with the aid of the mobile element (eighth smart home scenario).

5 **DETAILED DESCRIPTION**

Figure 1 shows a first telecommunication system TKS1 for wireless communication and telecommunication in a smart home environment. The first telecommunication system TKS1 has a base station BS preferably configured as a cordless base station, which is connected via a circuit connection a/b to a circuit-switched network PVN, which can for  
10 example be configured as an ISDN or PSTN network, and with an additional xDSL or ETHERNET connection to a packet-switched network PVN, which can for example be configured as the Internet. Telecommunication system TKS1 also includes at least one mobile element MT, configured as a cordless mobile element and a corded mobile element, which is connected bi-directionally to the base station BS via an air interface LSS or via a  
15 line interface LTSS respectively for EXTERNAL communication to provide access to the circuit-switched network LVN and/or the packet-switched network PVN and/or for INTERNAL communication between the mobile elements in the telecommunication system.

EXTERNAL communication includes short messages being transmitted according to the Short Message Service SMS and/or multimedia messages being transmitted according to  
20 the Multimedia Message Service MMS between the base station BS and/or the mobile elements MT and a service center DZ. As such, a subscriber in the first telecommunication system TKS1 may send such a message to a remote telecommunication subscriber or the telecommunication subscriber may receive such a message from the remote telecommunication subscriber.

25 With INTERNAL communication, the mobile elements generally communicate via the base station BS, with the base station assuming control of the communication

SUBSTITUTE SPECIFICATION - MARKED

(connection) and simply forwarding the data to be transmitted for the actual useful data transmission. It is however also possible for the mobile elements, which are connected via the air interface LSS to the base station BS, to transmit the data mutually without involving the base station BS in the course of a so-called point to point connection, where they are  
5 responsible both for controlling the connection and for the actual useful data transmission.

The cordless mobile elements MT of the first telecommunication system TKS1, which are connected via the air interface LSS to the cordless base station BS, are either cordless INPUT/OUTPUT mobile boxes MB, so-called cordless I/O mobile boxes, or telecommunication handsets TKHA configured as cordless user-friendly telephone handsets  
10 with a user interface (operator interface) comprising a keypad or voice control as well as a display device with menu control, while the corded mobile element MT, which is connected via the line interface LTSS to the base station BS, is illustrated as a corded set-top box STB.

As an alternative to the first telecommunication system TKS1 shown in figure 1, the telecommunication system can be modified such that, instead of the cordless user-friendly  
15 telephone handset, a mobile telephone with the same or comparable features (e.g. a GSM or 3GPP mobile) is used with a cordless interface for cordless connection to the cordless base station BS and to the other cordless mobile elements MT.

In a further modification it is also possible for the cordless base station BS also to be replaced by a mobile radio base station. This means that INTERNAL communication is such  
20 a telecommunication system is exclusively wireless communication from cordless mobile element to cordless mobile element or from cordless mobile telephone to the mobile telephone with the cordless interface in the course of a point to point connection, without involving the mobile radio base station. EXTERNAL communication in this telecommunication system from the mobile telephone to the external network takes place, as  
25 in mobile radio, via the mobile radio base station, while EXTERNAL communication from the other cordless mobile elements MT takes place both via the mobile telephone and the



SUBSTITUTE SPECIFICATION - MARKED

mobile radio base station, with the mobile telephone thereby operating as a cordless/mobile radio converter.

The different I/O mobile boxes MB and the set-top box in the first telecommunication system TKS1 are connected to various devices and equipment for the smart home scenario.

5 Thus an I/O mobile box MB, configured as a first mobile element MT1, is connected via a circuit connection USB, ETHERNET to a personal computer PC. Instead of connecting the personal computer PC via the circuit connection USB, ETHERNET to the first mobile element MT1 or the I/O mobile box MB, an integration solution is also possible, in which an I/O mobile box card MBK configured as a first mobile element MT1 with a PCI (Peripheral  
10 Component Interconnect) bus interface is housed on a free PCI card slot of the personal computer PC.

Multiple (such as four) I/O mobile boxes MB are also connected as ~~second~~further first mobile elements MT[[2]]1 to a television FA, a HIFI unit HA and two electrical appliances ELG, a washing machine and an electric cooker. While the connection between  
15 the television FA and the ~~second~~first mobile element MT[[2]]1 is preferably a circuit connection SCART S-VIDEO (Syndicat des Constructeurs d'Appareils Radiorécepteurs et Téléviseurs; Super-Video) and the connection between the HIFI unit HA and the ~~second~~first mobile element MT[[2]]1 is preferably a circuit connection CINCH, S/PDIF (standard connection originating from the CINCH company for transmitting electrical signals, used on  
20 coaxial cables; Sony/Philips Digital InterFace), the connection between the two electrical appliances ELG, the washing machine and the electric cooker, are preferably a circuit connection EIB, LON, LCN, KNX (European Installation Bus - a standard bus for building installations to control all types of technical device; Local Operating Network - a field bus system by the US company Echolon; Local Control Network - a bus system from the  
25 Issendorf company; KoNeX standard), in which the power of the three bus systems EIB, BatiBus and EHS is combined, thereby guaranteeing interoperability, where BatiBus is a bus system developed in France, similar in structure to the EIB bus and where EHS is an

SUBSTITUTE SPECIFICATION - MARKED

10

association of a number of European companies to produce the European Home System. All the circuit connections specified SCART, S-VIDEO, CINCH, S/PDIF, EIB, LON, LCN KNX are standard interfaces used in domestic technology and electronic maintenance systems.

5 It should be pointed out here that the integration solution discussed with the I/O mobile box <---> personal computer assignment is of course also possible with the television FA, the HIFI unit HA and the electrical appliances ELG.

10 The electrical appliances ELG, the television FA, the HIFI unit HA, the personal computer PC, the base station BS and the I/O mobile boxes MB configured as the first ~~and second~~ mobile ~~elements~~element MT1, ~~MT2~~ are all connected to a power supply network for power supply purposes.

15 In contrast to this, the telecommunication handsets TKHA, configured as ~~third~~second mobile elements MT[[3]]2 and also connected to the base station BS via the air interface LSS, are battery operated, while the set-top box STB belonging to the ~~second~~first mobile elements MT[[2]]1 and connected to the base station BS via line interface LTSS and is connected to the power supply network SVN like the I/O mobile boxes MB. The set-top box STB receives a DVB[[.]] signal DVB-T/S/C (Digital Video Broadcasting - Terrestrial/Satellite/Cable) and converts said DVB signal to an Analog Signal/Digital Signal AS/DS for the television FA and the HIFI unit HA.

20 In the first telecommunication system TKS1, video and/or control data TAVS is now transmitted ~~between the mobile elements MT1, MT2, MT3 and the base station BS,~~during "smart home" scenarios between the mobile elements MT1, MT2, ~~MT3~~ and the base station BS, between the mobile elements MT1, MT2 and between the mobile elements MT1, MT2, ~~MT3~~ and the base station BS, as well as the circuit-switched network LVN and the packet-switched network PVN, including the service center DZ assigned to  
25 these networks. ~~The~~Because, the data can be transmitted from any device or any equipment in the first telecommunication system TKS1 to another device or other equipment in the

SUBSTITUTE SPECIFICATION - MARKED

11

telecommunication system TKS1. ~~Accordingly, and~~ these devices or equipment operate as data source/data sink, such as the personal computer PC, the television FA, the HIFI unit HA and the electrical appliances ELG as well as the service center DZ. ~~The, the~~ personal computer PC is referred to as the first INTERNAL data source/data sink I-DQS1 because of  
5 its locational local proximity to the base station BS and its assignment to the first mobile element MT1. The television FA, HIFI unit HA and electrical appliances ELG are referred to as the second INTERNAL data source/data sink I/DQS2 also due to their locational local proximity to the base station BS and their assignment to the ~~second~~first mobile element MT[[2.]]1. The service center DZ is referred to as the EXTERNAL data source/data sink E-  
10 DQS due to its association with the circuit-switched network LVN and the packet-switched network PVN and therefore its locational local remoteness from the base station BS.

It is understood that the mobile elements MT1, MT2, ~~MT3~~ and the base station BS can be configured as further data sources/data sinks.

The text, audio, video and/or control data TAVS transmitted in the first  
15 telecommunication system TKS1 for the smart home scenario can be supplied as follows:

The text data is preferably short messages according to the Short Message Service or video text information.

The audio data is preferably telephone call information, music information according to the Multimedia Message Service or audio downloads from the internet, e.g. MP3 files.

20 The video data is preferably image information according to the Multimedia Message Service or video downloads from the internet.

The control data finally is data for controlling, measuring, regulating, calibrating, diagnosing and/or maintaining electrical appliances.

To tailor the physical resources of the first telecommunication system TKS1 for  
25 wireless communication and telecommunication in the smart home environment optimally to

SUBSTITUTE SPECIFICATION - MARKED

12

the data to be transmitted (e.g. voice and text data on the one hand and packet, audio and video data on the other hand) and the quantity of data generally associated therewith, the first telecommunication system TKS1 is preferably designed such that different air interfaces that are optimally designed for the respective data transmission are available for the different types of data mentioned. The air interface LSS can therefore include a shared interface for telephony and broadband data transmission or a separate interface for telephony and broadband data transmission respectively.

The air interface LSS may be an interface based on DECT, WDCT, DECT and Bluetooth, VWDCT and Bluetooth, DECT and IEEE 802.11 a, DECT and IEEE 802.11b, DECT and IEEE 802.11 g, WDCT and IEEE 802.11 a, WDCT and IEEE 802.11b, WDCT and IEEE 802.11 g, GSM and DECT, GSM and Bluetooth, GSM and IEEE 802.11 a, GSM and IEEE 802.11 b, GSM and IEEE 802.11 g, 3GPP and Bluetooth, 3GPP and IEEE 802.11 a, 3GPP and IEEE 802.11 b or 3GPP and IEEE 802.11 g, or any similar standard that is known in the art.

Figure 2 shows a second telecommunication system TKS2 for wireless communication and telecommunication in a smart home environment. The second telecommunication system TKS2, like the first telecommunication system TKS1 in figure 1, again has a base station BS preferably configured as a cordless base station, connected via a circuit connection alb to a circuit-switched network PVN, which can for example be configured as an ISDN or PSTN network, and with an additional xDSL or ETHERNET connection to a packet-switched network PVN. System TKS2 is further connected to at least one mobile element MT configured as a cordless mobile element, which is connected bi-directionally to the base station via an air interface LSS in each instance for EXTERNAL communication - access to the circuit-switched network LVN and/or the packet-switched network PVN - and/or for INTERNAL communication - communication between the mobile elements in the telecommunication system.

SUBSTITUTE SPECIFICATION - MARKED

13

EXTERNAL communication can again be short messages being transmitted according to the Short Message Service SMS and/or multimedia messages being transmitted according to the Multimedia Message Service MMS between the base station BS and/or the mobile elements MT and a service center DZ. Accordingly, a subscriber in the first  
5 telecommunication system TKS1 may send such a message to a remote telecommunication subscriber, or the telecommunication system subscriber may receive such a message from the remote telecommunication subscriber.

With INTERNAL communication, the mobile elements involved generally communicate via the base station BS, with the base station assuming control of the  
10 communication (connection) and simply forwarding the data to be transmitted for the actual useful data transmission. It is however also possible for the mobile elements, which are connected via the air interface LSS to the base station BS, to transmit the data mutually without involving the base station BS in the course of a so-called point to point connection, where they are responsible both for controlling the connection and for the actual useful data  
15 transmission.

The cordless mobile elements MT of the second telecommunication system TKS2, which are connected via the air interface LSS to the cordless base station BS, are again either cordless INPUT/OUTPUT mobile boxes MB, so-called cordless I/O mobile boxes, a cordless set-top box STB with known functionality or telecommunication handsets TKHA configured  
20 as cordless user-friendly telephone handsets with a user interface (operator interface) comprising a keypad or voice control as well as a display device with menu control.

As an alternative to the second telecommunication system TKS2 shown in figure 2, a telecommunication system can be modified such that, instead of the cordless user-friendly telephone handset, a mobile telephone with the same or comparable features (e.g. a GSM or  
25 3GPP mobile) is used with a cordless interface for cordless connection to the cordless base station BS and to the other cordless mobile elements MT.



SUBSTITUTE SPECIFICATION - MARKED

14

The different I/O mobile boxes MB and the set-top box STB in the second telecommunication system TKS2 are again connected to various devices and equipment for the smart home scenario. In contrast to the first telecommunication system TKS1 however, a personal computer PC is now connected via a circuit connection USB, ETHERNET not to an I/O mobile box MB configured as a first mobile element MT1 but directly to the cordless base station BS.

Multiple **(here four)** I/O mobile boxes MB are also connected as **secondfurther first** mobile elements MT[[2]]1 to a television FA, a HIFI unit HA and two electrical appliances ELG, a washing machine and an electric cooker. While the connection between the television FA and the **secondfirst** mobile element MT[[2]]1 is again preferably a circuit connection SCART, S-VIDEO and the connection between the HIFI unit HA and the **secondfirst** mobile element MT[[2]]1 is again preferably a circuit connection CINCH, S/PDIF, the connection between the two electrical appliances ELG, the washing machine and electric cooker, is again preferably a circuit connection EIB, LON, LCN, KNX.

It should be pointed out here that the direct connection option discussed with the base station <---> personal computer assignment is of course also possible with the television FA, the HIFI unit HA and the electrical appliances ELG.

The electrical appliances ELG, the television FA, the HIFI unit HA, the personal computer PC, the base station BS and the I/O mobile boxes MB, configured as the second mobile element MT2, are again all connected to a power supply network SVN for power supply purposes.

Telecommunication handsets TKHA, are configured as **thirdsecond** mobile elements **MT2** and are also connected to the base station BS via the air interface LSS, and are again battery operated, while the set-top box STB belonging to the **secondfirst** mobile elements MT[[2]]1 and connected to the base station BS via the air interface LSS is connected to the power supply network SVN like the I/O mobile boxes MB. The set-top box STB again

SUBSTITUTE SPECIFICATION - MARKED

15

receives a DVB signal DVB-T/S/C and converts said DVB signal to an Analog Signal/Digital Signal AS/DS for the television FA and the HIFI unit HA.

5 In the second telecommunication system TKS2, as in the first telecommunication system TKS1, audio, video and/or control data TAVS is transmitted between the mobile elements MT~~2~~, ~~MT3~~1 and the base station BS, between the mobile elements MT[[2,]]1, MT[[3]]2 and between the mobile elements MT[[2,]]1, MT[[3]]2 and the base station BS on the one hand and the circuit-switched network LVN and the packet-switched network PVN including the service center DZ assigned to these networks on the other hand. As the data can again be transmitted from any device or any equipment in the second telecommunication system TKS2 to another device or other equipment in the telecommunication system TKS2, and these devices or equipment therefore operate as data source/data sink, such as the personal computer PC, the television FA, the HIFI unit HA and the electrical appliances ELG as well as the service center DZ. The personal computer PC is again referred to as the first INTERNAL data source/data sink I-DQS1 because of its locational proximity to the base station BS. The television FA, HIFI unit HA and electrical appliances ELG are again referred to as the second INTERNAL data source/data sink I/DQS2 also due to their locational proximity to the base station BS and their assignment to the ~~second-first~~ mobile element MT[[2,]]1. The service center DZ is again referred to as the EXTERNAL data source/data sink E-DQS due to its association with the circuit-switched network LVN and the packet-switched network PVN and therefore its locational local remoteness from the base station BS.

~~It is understood~~For the smart home scenario it is again possible that the mobile elements MT[[2,]]1, MT[[3]]2 and the base station BS may also be configured as further data sources/data sinks.

25 The text, audio, video and/or control data TAVS transmitted in the second telecommunication system TKS2 for the smart home scenario can again be supplied as follows:

SUBSTITUTE SPECIFICATION - MARKED

16

The text data is preferably short messages according to the Short Message Service or video text information.

The audio data is preferably telephone call information, music information according to the Multimedia Message Service or audio downloads from the internet, e.g. MP3 files.

5           The video data is preferably image information according to the Multimedia Message Service or video downloads from the internet.

The control data finally is data for controlling, measuring, regulating, calibrating, diagnosing and/or maintaining electrical appliances.

10           To tailor the physical resources of the second telecommunication system TKS2 for wireless communication and telecommunication in the smart home environment optimally again to the data to be transmitted (e.g. voice and text data on the one hand and packet, audio and video data on the other hand) and the quantity of data generally associated therewith, the second telecommunication system TKS2 is again preferably designed such that different air interfaces that are optimally designed for the respective data transmission are available for  
15           the different types of data mentioned. The air interface LSS can for example therefore again include a shared interface for telephony and broadband data transmission or again a separate interface for telephony and broadband data transmission respectively.

20           The air interface LSS may be based on DECT, WDCT, DECT and Bluetooth, WDCT and Bluetooth, DECT and IEEE 802.11a, DECT and IEEE 802.11b, DECT and IEEE 802.11g, WDCT and IEEE 802.11a, WDCT and IEEE 802.11b, WDCT and IEEE 802.11g, GSM and DECT, GSM and Bluetooth, GSM and IEEE 802.11a, GSM and IEEE 802.11b, GSM and IEEE 802.11g, 3GPP and Bluetooth, 3GPP and IEEE 802.11a, 3GPP and IEEE 802.11b or 3GPP and IEEE 802.11g, and any similar standard that is known in the art.

25           Figure 3 shows a third telecommunication system TKS3 for wireless communication and telecommunication in a smart home environment. For this the third telecommunication

SUBSTITUTE SPECIFICATION - MARKED

17

system TKS3 has a base station BS preferably configured as a network interface module NSSM in the form of a cordless base station card integrated in a personal computer PC. The base station BS is connected via a circuit connection a/b to a circuit-switched network PVN, which may be configured as an ISDN or PSTN network, and with an additional xDSL or  
5 ETHERNET connection to a packet-switched network PVN, . System TKS3 is further connected to at least one mobile element MT configured as a cordless mobile element and a corded mobile element, which is connected bi-directionally to the base station via an air interface LSS in each instance for EXTERNAL communication - access to the circuit-switched network LVN and/or the packet-switched network PVN - and/or for INTERNAL  
10 communication - communication between the mobile elements in the telecommunication system. The network interface module NSSM or base station card preferably has a PCI (Peripheral Component Interconnect) bus interface and is housed for this purpose on a free PCI card slot of the personal computer PC.

EXTERNAL communication can again involve short messages being transmitted  
15 according to the Short Message Service SMS and/or multimedia messages being transmitted according to the Multimedia Message Service MMS between the base station BS and/or the mobile elements MT and a service center DZ. Again a subscriber in the first telecommunication system TKS1 may send such a message to a remote telecommunication subscriber or the telecommunication system subscriber may receive such a message from the  
20 remote telecommunication subscriber.

With INTERNAL communication, the mobile elements involved generally communicate again via the base station BS, with the base station assuming control of the communication (connection) and forwarding the data to be transmitted for the actual useful data transmission. The mobile elements, which are connected via the air interface LSS to the  
25 base station BS, may again transmit the data mutually without involving the base station BS in the course of a so-called point to point connection, where they are responsible both for controlling the connection and for the actual useful data transmission.

SUBSTITUTE SPECIFICATION - MARKED

18

The cordless mobile elements MT of the third telecommunication system TKS3, which are connected via the air interface LSS to the cordless base station BS configured as a network interface module NSSM or base station card, are again either cordless INPUT/OUTPUT mobile boxes MB, so-called cordless I/O mobile boxes, an I/O & set-top mobile box MB, STB or telecommunication handsets TKHA configured as cordless user-friendly telephone handsets with a user interface (operator interface) comprising a keypad or voice control as well as a display device with menu control.

As an alternative to the third telecommunication system TKS3 shown in figure 3, a telecommunication system can be modified such that, instead of the cordless user-friendly telephone handset, a mobile telephone with the same or comparable features (e.g. a GSM or 3GPP mobile) is used with a cordless interface for cordless connection to the cordless base station BS and to the other cordless mobile elements MT.

The different I/O mobile boxes MB and the I/O & set-top mobile box MB, STB in the third telecommunication system TKS3 are again connected to various devices and equipment for the smart home scenario. Three I/O mobile boxes MB are therefore connected as ~~second~~first mobile elements MT[[2]]1 to a HIFI unit HA and two electrical appliances ELG, a washing machine and an electric cooker and the I/O & set-top mobile box MB, STB is connected to a television FA. The connection between the television FA and the ~~second~~first mobile element MT[[2]]1 is again preferably a circuit connection SCART, S-VIDEO and the connection between the HIFI unit HA and the second mobile element MT2 is again preferably a circuit connection CINCH, S/PDIF, the connection between the two electrical appliances ELG, the washing machine and electric cooker, is again preferably a circuit connection EIB, LON, LCN, KNX.

It should be pointed out here that the integration solution (network interface module or base station card) discussed with the base station <---> personal computer assignment is of course also possible with the television FA, the HIFI unit HA and the electrical appliances ELG.



SUBSTITUTE SPECIFICATION - MARKED

19

The electrical appliances ELG, the television FA, the HIFI unit HA, the personal computer PC, the base station BS and the I/O mobile boxes MB configured as the ~~second~~first mobile element MT[[2]]1 are all connected to a power supply network for power supply purposes.

5        ~~The~~In contrast, the telecommunication handsets TKHA are configured as ~~third~~second mobile elements MT[[3]]2 and also connected to the base station BS via the air interface LSS, are again battery operated, while the I/O and set-top mobile box MB, STB belonging to the ~~second~~first mobile elements MT[[2]]1 and connected to the base station BS via the air interface LSS is connected to the power supply network SVN like the I/O mobile  
10 boxes MB. The set-top box STB again receives a DVB signal DVB-T/S/C and converts said DVB signal in the known manner to an Analog Signal/Digital Signal AS/DS for the television FA and the HIFI unit HA.

In the third telecommunication system TKS3, as in the first and second telecommunication systems TKS1, TKS2, text, audio, video and/or control data TAVS is  
15 transmitted between the mobile elements MT[[2,]]1, MT[[3]]2 and the base station BS, between the mobile elements MT[[2,]]1, MT[[3]]2 and between the mobile elements MT[[2,]]1, MT[[3]]2 and the base station BS on the one hand and the circuit-switched network LVN and the packet-switched network PVN including the service center DZ assigned to these networks on the other hand. As the data can again be transmitted from any  
20 device or equipment in the third telecommunication system TKS3 to another device or other equipment in the telecommunication system TKS1 and these devices or equipment therefore operate as data source/data sink, such as the personal computer PC, the television FA, the HIFI unit HA and the electrical appliances ELG as well as the service center DZ. The personal computer PC is again referred to as the first INTERNAL data source/data sink I-  
25 DQS1 because of its structural unity with the base station BS. The television FA, HIFI unit HA and electrical appliances ELG are again also referred to as the second INTERNAL data source/data sink I/DQS2 due to their locational proximity to the base station BS and their

SUBSTITUTE SPECIFICATION - MARKED

20

assignment to the ~~second~~first mobile element MT[[2.]]1. The service center DZ is again referred to as the EXTERNAL data source/data sink E-DQS due to its association with the circuit-switched network LVN and the packet-switched network PVN and therefore its locational remoteness from the base station BS.

5           ~~It is understood~~For the smart home scenario it is again possible that the mobile elements MT[[2.]]1, MT[[3]]2 and the base station BS may be configured as further data sources/data sinks.

10           The text, audio, video and/or control data TAVS transmitted in the third telecommunication system TKS3 for the smart home scenario can again be supplied as follows:

          The text data is preferably short messages according to the Short Message Service or video text information.

          The audio data is preferably telephone call information, music information according to the Multimedia Message Service or audio downloads from the internet, e.g. MP3 files.

15           The video data is preferably image information according to the Multimedia Message Service or video downloads from the internet.

          The control data finally is data for controlling, measuring, regulating, calibrating, diagnosing and/or maintaining electrical appliances.

20           To tailor the physical resources of the third telecommunication system TKS3 for wireless communication and telecommunication in the smart home environment again optimally to the data to be transmitted (e.g. voice and text data on the one hand and packet, audio and video data on the other hand) and to the quantity of data generally associated therewith, the third telecommunication system TKS3 is again preferably configured such that different air interfaces that are optimally designed for the respective data transmission are  
25           available for the different types of data mentioned. The air interface LSS may therefore again

SUBSTITUTE SPECIFICATION - MARKED

21

include a shared interface for telephony and broadband data transmission or again a separate interface for telephony and broadband data transmission respectively.

It is understood that the air interface LSS may be an interface based on DECT, WDCT, DECT and Bluetooth, WDCT and Bluetooth, DECT and IEEE 802.11 a, DECT and  
5 IEEE 802.11b, DECT and IEEE 802.11g, WDCT and IEEE 802.11 a, WDCT and IEEE 802.11b, WDCT and IEEE 802.11g, GSM and DECT, GSM and Bluetooth, GSM and IEEE 802.11 a, GSM and IEEE 802.11b, GSM and IEEE 802.11g, 3GPP and Bluetooth, 3GPP and IEEE 802.11 a, 3GPP and IEEE 802.11b or 3GPP and IEEE 802.11g or any other similar standards known in the art.

10 Figure 4 shows a first message sequence chart according to a first smart home scenario, in which the user of a ~~third~~second mobile element MT[[3]]2 of the telecommunication systems TKS1, TKS2, TKS3 shown in figures 1 to 3. configured as a telecommunication handset TKHA uses mobile element MT32 to wake up the personal computer PC from standby mode and start it up. The message sequence required for this  
15 operates according to figure 4 between the ~~third~~second mobile element MT[[3,]]2, the first mobile element MT 1 connected to the ~~third~~second mobile element MT[[3]]2 via the air interface LSS and configured as an I/O mobile box MB or an I/O mobile box card MBK and the personal computer PC connected to the first mobile element MT1 via the circuit connection USB, ETHERNET and configured as the first INTERNAL data source/data sink  
20 I-DQS1.

The units or components taken into account to represent the message sequence are:

-(i) for the mobile element MT[[3]]2 a user interface BSS, preferably having a keypad TA and a display device AV configured as a display screen, an MT storage unit MT-S, a central control unit MT-P configured as an MT processor and a shared MT/MB air interface  
25 MT/MB-LSS operating between the mobile element MT[[3]]2 and the I/O mobile box MB, which are connected together in the manner shown,

SUBSTITUTE SPECIFICATION - MARKED

22

(ii) for the I/O mobile box, the MT/MB air interface MT/MB-LSS shared with the mobile element MT[[3,]]2, a central control unit MB-P configured as an MB processor and a USB/ETHERNET interface USB/ETH-SS, which are connected together in the manner shown, and

5 (iii) for the personal computer PC, as with the I/O mobile box MB, a USB/ETHERNET interface USB/ETH-SS, a power manager PM, a central control unit PC-P configured as a PC processor and a PC storage unit PC-S, which are connected together in the manner shown.

10 In an initial state AZ of the message sequence chart applicable to all units and components, the personal computer PC is in standby mode and is woken up from this state by the mobile element MT[[3,]]2 and started up. To this end a control command "Wake up and start PC" STK is transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. To set up an internal communication connection, the MT processor MT-P transmits a set-up message "Internal communication connection" AUM via the MT/MB air  
15 interface MT/MB-LSS to the MB processor MB-P. The MB processor MB-P then sends a confirmation message BM via the MT/MB air interface MT/MB-LSS back to the MT processor MT-P. The MT processor MT-P then transmits the command data "Wake up and start PC" KD belonging to the control command "Wake up and start PC" via the MT/MB air interface MT/MB-LSS, the MB processor MB-P, the USB/ETHERNET interface USB/ETH-  
20 SS in the I/O mobile box MB and the personal computer PC to the power manager PM. The power manager PM transmits a response message "PC woken up and started" AWM in the reverse direction via the same route to the MT processor MT-P. The MT processor MT-P then outputs display data "PC woken up and started" AD to the display screen AV of the user interface BSS, where said data is displayed. To cancel the internal communication connection  
25 that has been set up, the MT processor MT-P then transmits a cancellation message "Internal communication connection" ABM via the MT/MB air interface MB/MT-LSS to the MB

SUBSTITUTE SPECIFICATION - MARKED

23

processor MB-P, which responds to it in the reverse direction via the same route with a further confirmation message BM, as a result of which the connection is canceled.

Figures 5a to 5c show a second message sequence chart according to a second smart home scenario, in which the user of the ~~third~~second mobile element MT[[3]]2 of the telecommunication systems TKS1, TKS2, TKS3 shown in figures 1 to 3 configured as a telecommunication handset TKHA uses said mobile element MT[[3]]2 to display and process a multimedia message terminated in the base station BS and to create a new multimedia message. The message sequence required for this operates according to figures 5a to 5c between the circuit-switched and/or packet-switched network LVN, PVN, the base station BS connected to the network LVN, PVN via the circuit connection a/b, xDSL, ETHERNET and the ~~third~~second mobile element MT[[3]]2 connected to the base station BS via the air interface LSS.

The units or components taken into account to represent the message sequence are:

-(i) for the base station BS, a line and network connection LNA, a central control unit BS-P configured as a BS processor, a BS storage unit BS-S and a shared BS/MT air interface BS/MT-LSS operating between the base station BS and the mobile element MT[[3,]]2, which are connected together in the manner shown, and

(ii) for the ~~third~~second mobile element MT[[3]]2 the BS/MT air interface BS/MT-LSS shared with the base station BS, a central control unit MT-P configured as an MT processor, an MT storage unit MT-S and a user interface BSS, having for example a keypad TA and a display device AV configured as a display screen, with the components of the mobile element MT[[3]]2 being connected together in the manner shown.

In an initial state AZ of the message sequence chart applicable to all units and components, a multimedia message MMN is received by the base station BS (termination of message in the base station) and receipt of the multimedia message MMN is displayed on the mobile element MT[[3,]]2. To this end the multimedia message MMN is transmitted from the



SUBSTITUTE SPECIFICATION - MARKED

24

circuit-switched/packet-switched network LVN, PVN via the line and network connection LNA to the BS processor BS-P. The BS processor BS-P stores MMN data MMN-D corresponding to the multimedia message MMN in the BS storage unit BS-S. The BS processor BS-P then sends a broadcast message "New multimedia message" BCM via the  
5 BS/MT air interface BS/MT-LSS to the MT processor MT-P. The MT processor MT-P then outputs display information "Multimedia message available" AI to the display screen AV of the user interface BSS, where said information is displayed.

In a subsequent first consequential state FZ1 of the message sequence chart applicable to all units and components apart from the line and network connection LNA, a specific (nth)  
10 multimedia message MMN terminated in the base station BS is selected by the mobile element MT[[3]]2 and displayed on it. To this end a control command "MMN list" STK is transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P sends a request message "MMN list" AFM via the BS/MT air interface BS/MT-LSS to the BS processor BS-P. As a result of this request message the BS processor  
15 BS-P reads all the MMN data from the BS storage unit BS-S. After this reading process, the BS processor BS-P sends a response message AWM with an MMN data list MMN-DL via the BS/MT air interface BS/MT-LSS to the MT processor MT-P. In the MT processor MT-P the MMN data list MMN-DL is buffered in the MT storage unit MT-S and output to the display screen AV of the user interface BSS, where the MMN data list MMN-DL is  
20 displayed. A control command "nth MMN from list" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P then sends a request message "nth MMN from list" AFM via the BS/MT air interface BS/MT-LSS to the BS processor BS-P. As a result of this received request message the BS processor BS-P reads the nth MMN data from the BS storage unit BS-S. After the end of the  
25 reading process the BS processor BS-P transmits the read nth MMN data n-MMN-D in a response message AWM via the BS/MT air interface BS/MT-LSS to the MT processor MT-P. The MT processor MT-P stores the transmitted nth MMN data n-MMN-D in the MT

SUBSTITUTE SPECIFICATION - MARKED

25

storage unit MT-S and outputs it to the display screen AV of the user interface BSS where said data or the nth multimedia message is displayed.

In a subsequent second consequential state FZ2 of the message sequence chart applicable to the units and components "MT processor, MT storage unit, user  
5 interface/display and user interface/keypad" a displayed multimedia message, e.g. the nth multimedia message, is modified. To this end a control command "Modify nth MMN" STK is transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. After the control command STK has been transmitted, modification commands AEK are sent from the keypad TA to the MT processor MT-P. As a result of these modification commands AEK,  
10 the MT processor MT-P generates a modification message, which is stored in the MT storage unit MT-S and output to the display screen AV of the user interface BSS, where the modification message AEN is displayed.

In a subsequent state FZ3 of the message sequence chart again applicable to all units and components, a displayed multimedia message, e.g. the modified nth multimedia message,  
15 is answered. To this end a control command "Answer nth MMN" STK is transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. After transmission of the control command STK, response commands BAK are transmitted from the keypad TA to the MT processor MT-P. As a result of these response commands BAK, the MT processor MT-P generates a response message AWN, which is stored in the MT storage unit MT-S and output  
20 to the display screen AV of the user interface BSS, where the response message AWN is displayed. A control command "Send response message" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P reads response data AWD in the response message ANN from the MT storage unit MT-S and transmits the response data AWD via the BS/MT air interface BS/MT-LSS and the BS  
25 processor BS-P to the line and network connection LNA, from which the response message AWN corresponding to the response data AWD is sent to the circuit-switched/packet-switched network LVN, PVN.

SUBSTITUTE SPECIFICATION - MARKED

26

In a subsequent state FZ4 of the message sequence chart, again applicable to all units and components, a multimedia message is created from message elements or message components from the storage unit BS-S in the base station BS and then sent. To this end a control command "MMN menu" STK is transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P then sends a request message "MMN elements" AFM via the BS/MT air interface BS/MT-LSS to the BS processor BS-P. As a result of this request message the BS processor BS-P reads all the MMN data elements from the BS storage unit BS-S. After this reading process the BS processor BS-P sends a response message AWM with MMN data elements MMN-DE via the BS/MT air interface BS/MT-LSS to the MT processor MT-P. In the MT processor MT-P an MMN menu MMN-M is generated from the MMN data elements MMN-DE. This menu is buffered in the MT storage unit MT-S and output to the display screen AV of the user interface BSS, where the MMN menu MMN-M is displayed. MMN create commands MMN-EK are then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P creates an MMN message MMN-N from these MMN create commands, which is stored in the MT storage unit MT-S and output to the display screen AV of the user interface BSS where the MMN message MMN-N is displayed. A control command "Send MMN message" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P reads MMN data MMN-D corresponding to the MMN message from the MT storage unit MT-S and transmits the MMN data MMN-D via the BS/MT air interface BS/MT-LSS and the BS processor BS-P to the line and network connection LNA, from which the multimedia message MMN corresponding to the MMN data MMN-D is sent to the circuit-switched/packet-switched network LVN, PVN.

Figure 6 shows a third message sequence chart according to a third smart home scenario, in which the user of the ~~third~~second mobile element MT[[3]]2 of the telecommunication systems TKS1, TKS2, TKS3 shown in figures 1 to 3 is configured as a telecommunication handset TKHA and uses mobile element MT[[3]]2 to receive a multimedia message, i.e. to terminate a multimedia message in said mobile element MT[[3]]2

SUBSTITUTE SPECIFICATION - MARKED

27

and display it. The message sequence required for this operates according to figure 6 between the circuit-switched and/or packet-switched network LVN, PVN, the base station BS connected to the network LVN, PVN via the circuit connection a/b, xDSL, ETHERNET and the ~~third~~second mobile element MT[[3]]2 connected to the base station BS via the air interface LSS.

The units or components taken into account to represent the message sequence are

(i) for the base station BS, a line and network connection LNA, a central control unit BS-P configured as a BS processor, a BS storage unit BS-S, and a shared BS/MT air interface BS/MT-LSS operating between the base station BS and the mobile element MT[[3,]]2, which are connected together in the manner shown, and

(ii) for the ~~third~~second mobile element MT[[3]]2 the BS/MT air interface BS/MT-LSS shared with the base station BS, a digital network interface DNA (e.g., as a modem or ISDN-Dchannel), a central control unit MT-P configured as an MT processor, an MT storage unit MT-S and a user interface BSS, having a keypad TA and a display device AV configured as a display screen for example, with the components of the mobile element MT3 being connected together in the manner shown.

In an initial state AZ of the message sequence chart applicable to all units and components, a multimedia message MMN is received by the mobile element MT[[3]]2 (termination of message in the mobile element) and receipt of the multimedia message MMN is displayed on the mobile element MT[[3,]]2. To this end the multimedia message MMN is transmitted from the circuit-switched/packet-switched network LVN, PVN via the line and network connection LNA to the BS processor BS-P, whereupon the BS processor BS-P then sends a broadcast message "New multimedia message" BCM via the BS/MT air interface BS/MT-LSS and the digital network interface DNA to the MT processor MT-P. The MT processor MT-P then outputs display information "Multimedia message available" AI to the display screen AV of the user interface BSS, where said information is displayed. A control



SUBSTITUTE SPECIFICATION - MARKED

28

command "Set up communication connection to MMN service center" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. To set up a communication connection to the MMN service center, the MT processor MT-P transmits a set-up message "Communication connection to MMN service center" AUM via  
5 the digital network interface DNA and the BS/MT air interface BS/MT-LSS to the BS processor BS-P. The BS processor BS-P then sets up the communication connection to the MMN service center in the circuit-switched/packet-switched network LVN, PVN via the line and network connection LNA. If the BS processor BS-P then receives confirmation of the setting up of the communication connection via the line and network connection LNA from  
10 the circuit-switched/packet-switched network LVN, PVN, it sends a confirmation message "Setting up of communication connection" BM via the BS/MT air interface BS/MT-LSS and the digital network interface DNA to the MT processor MT-P.

A control command "Retrieve multimedia message" STK is then transmitted from the keyboard TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P  
15 then sends a request message "Retrieve multimedia message" AFM via the digital network interface DNA and the BS/MT air interface BS/MT-LSS to the BS processor BS-P. The BS processor BS-P then retrieves the multimedia message from the circuit-switched/packet-switched network LVN, PVN via the line and network connection LNA and the communication connection to the MMN service center. If the BS processor BS-P then  
20 receives MMN data MMN-D from the circuit-switched/packet-switched network LVN, PVN via the line and network connection LNA, it sends a response message AWM with the MMN data MMN-D via the BS/MT air interface BS/MT-LSS and the digital network interface DNA to the MT processor MT-P. The MT processor MT-P stores the transmitted MMN data MMN-D in the MT storage unit MT-S and outputs it to the display screen AV of the user  
25 interface BSS, where said data or the multimedia message is displayed. To cancel the communication connection to the MMN service center, the MT processor MT-P then transmits a cancellation message "Communication connection to MMN service center" ABM via the digital network interface DNA and the BS/MT air interface BS/MT-LSS to the BS



SUBSTITUTE SPECIFICATION - MARKED

29

processor BS-P. The BS processor BS-P then cancels the communication connection to the MMN service center in the circuit-switched/packet-switched network LVN, PVN via the line and network connection LNA. If the BS processor BS-P then receives confirmation of the cancellation of the communication connection via the line and network connection LNA from  
5 the circuit-switched/packet-switched network LVN, PVN, it sends a confirmation message "Cancellation of communication connection" BM via the BS/MT air interface BS/MT-LSS and the digital network interface DNA to the MT processor MT-P, as a result of which the connection is canceled.

Figures 7a and 7b show a fourth message sequence chart according to a fourth smart  
10 home scenario, in which the user of the ~~third~~second mobile element MT[[3]]2 of the telecommunication systems TKS1, TKS2, TKS3 shown in figures 1 to 3 configured as a telecommunication handset TKHA transmits a specific (nth) multimedia message internally from said mobile element MT[[3]]2 to another mobile element, e.g. the first mobile element MT1, ~~the second mobile element MT2~~1 or a further ~~third~~second mobile element  
15 MT[[3.]]2. The message sequence required for this operates according to figures 7a and 7b between the ~~third~~second mobile element MT[[3]]2 and the further mobile element MT I, MT2, ~~MT3~~ connected to this directly via the air interface LSS (point to point connection) or indirectly via the base station BS.

The units or components taken into account to represent the message sequence  
20 are~~[00108]~~—(i) for the mobile element MT[[3]]2 a user interface BSS, having a keypad TA and a display device AV configured as a display screen for example, an MT storage unit MT-S, a central control unit MT-P configured as an MT processor and a shared MT/MT air interface MT/MT-LSS operating between the mobile element MT[[3]]2 and the further mobile element MT1, MT2, ~~MT3~~, which are connected together in the manner shown, and

25 (ii) for the further mobile element MT1, MT2, ~~MT3~~ the MT/MT air interface MT/MT-LSS shared with the ~~third~~second mobile element MT[[3.]]2, a central control unit MT-P configured as an MT processor, an MT storage unit MT S and a user interface BSS,

SUBSTITUTE SPECIFICATION - MARKED

30

having for example a keypad TA and a display device AV configured as a display screen, with the components of the mobile element MT~~3~~2 being connected together in the manner shown.

5 In an initial state AZ of the message sequence chart applicable to all units and components, an nth multimedia message MMN is transmitted internally from the ~~third~~ second mobile element MT[[3]]2 to a further mobile element MT1, MT2, ~~MT3~~. To this end a control command "MMN list" STK is transmitted from the keyboard TA of the user interface BSS to the MT processor MT-P. The MT processor then reads all the MMN data from the MT storage unit MT-S. After this reading process the MT processor MT-P outputs  
10 an MMN list MMN-L to the display screen AV of the user interface BSS, where said MMN list MMN-L is displayed. A control command "nth MMN from list" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P then reads nth MMN data n-MMN-D from the MT storage unit MT-S. After the end of the reading process the MT processor MT-P outputs the read nth MMN data n-MMN-D to  
15 the display screen AV of the user interface BSS, where said data is displayed. A control command "Send nth MMN data to further mobile element" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. To cancel an internal communication connection, the MT processor MT-P transmits a cancellation message "Internal communication connection" AUM via the MT/MT air interface MT/MT-LSS to the  
20 MT processor MT-P of the further mobile element MT1, MT2, ~~MT3~~. This MT processor MT-P then sends a confirmation message BM via the MT/MT air interface MT/MT-LSS back to the MT processor MT-P of the ~~third~~ second mobile element MT[[3.]]2. The MT processor MT-P then sends a request message "Transmit nth MMN data?" AFM via the MT/MT air interface MT/MT-LSS to the MT processor MT-P of the further mobile element  
25 MT1, MT2, ~~MT3~~. In response this MT processor MT-P sends a response message "Agreed" AWM via the MT/MT air interface MT/MT-LSS back to the MT processor MT-P of the ~~third~~ second mobile element MT[[3.]]2. As a result of this response message AWM the MT processor MT-P reads the nth MMN data n-MMN-D from the MT storage unit MT-S. After

SUBSTITUTE SPECIFICATION - MARKED

31

this reading process the MT processor MT-P sends a transmission message UM with the nth MMN data n-MMN-D via the MT/MT air interface MT/MT-LSS to the MT processor MT-P of the further mobile element MT 1, MT2,~~MT3~~. This MT processor MT-P then stores the nth MMN data n-MMN-D in the MT storage unit MT-S and optionally outputs it to the display  
5 screen AV of the user interface BSS, where said data can be displayed. The MT processor MT-P then sends a confirmation message "Data received" BM via the MT/MT air interface MT/MT-LSS to the MT processor MT-P of the ~~third~~second mobile element MT[[3,]]2. As a result of this received confirmation message BM the MT processor MT-P outputs display information "nth MMN data successfully transmitted" AI to the display screen AV of the user  
10 interface BSS of the ~~third~~second mobile element MT[[3,]]2, where the information is displayed. A control command "Terminate connection" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P of the ~~third~~second mobile element MT[[3,]]2, whereupon, to cancel the internal communication connection that has been set up, the MT processor MT-P sends a cancellation message "Internal communication  
15 connection" ABM via the MT/MT air interface MT/MT-LSS to the MT processor MT-P of the further mobile element MT 1, MT2,~~MT3~~, which responds to this in the reverse direction via the same route with a further confirmation message BM, as a result of which the connection is canceled.

Figures 8a to 8b show a fifth message sequence chart according to a fifth smart home  
20 scenario, in which the user of the ~~third~~second mobile element MT[[3,]]2 of the telecommunication systems TKS1, TKS2, TKS3 shown in figures 1 to 3, configured as a telecommunication handset TKHA, watches a video film, which is stored on the personal computer PC, on the television FA. The message sequence required for this operates according to figures 8a to 8c between the third mobile element MT3, the personal computer  
25 PC connected directly to the third mobile element MT3 via the air interface LSS (point to point connection) or indirectly via the base station BS, with the integrated I/O mobile box card MBK according to figures 1 and 3, the I/O mobile box MB connected to the personal

SUBSTITUTE SPECIFICATION - MARKED

32

computer PC via the air interface LSS and the television FA connected to the I/O mobile box MB via the circuit connection SCART, S-VIDEO.

The units or components taken into account to represent the message sequence are

(i) for the mobile element MT[[3]]2 a user interface BSS, having a keypad TA and a display device AV configured as a display screen for example, an MT storage unit MT-S, a central control unit MT-P configured as an MT processor and a shared PC/MT air interface PC/MT-LSS operating between the mobile element MT[[3]]2 and the personal computer PC with the integrated I/O mobile box card MBK, which are connected together in the manner shown,

(ii) for the personal computer with the integrated I/O mobile box card MBK the PC/MT air interface PC/MT-LSS shared with the mobile element MT[[3,]]2, a central control unit MT-P configured as an MT processor, a PC storage unit PC-S and a shared PC/MB air interface PC/MB-LSS operating between the personal computer PC with the integrated I/O mobile box card MBK and the I/O mobile box MB, which are connected together in the manner shown,

(iii) for the PO mobile box MB the PC/MB air interface PC/MB-LSS shared with the personal computer PC with the integrated I/O mobile box card MBK, a central control unit MB-P configured as an MB processor, an MB storage unit MB-S and a shared data interface DSS operating between the I/O mobile box MB and the television FA, which are connected together in the manner shown,

(iv) for the television FA the data interface DSS shared with the I/O mobile box MB, a central control unit FA-P configured as an FA processor and an FA screen FA-B, which are connected together in the manner shown.

In an optional preliminary state VZ of the message sequence chart, applicable to all units and components, both the personal computer PC and the television FA can be in

SUBSTITUTE SPECIFICATION - MARKED

33

standby mode and be woken up and started up from this state by the mobile element MT[[3]]2 according to the wake-up procedure described in figure 4. In a subsequent initial state AZ of the message sequence chart applicable to all units and components, a video film stored in the personal computer PC is output on the television FA. To this end a control  
5 command "Video list" STK is transmitted from the keypad TA of the user interface BSS by the MT processor MT-P. The MT processor MT-P transmits a request message "Video list" AFM via the PC/MT air interface PC/MT-LSS to the PC processor PC-P. As a result of this request message AFM the PC processor PC-P reads all the video data from the PC storage unit PC-S. After this reading process the PC processor PC-P sends a response message AWM  
10 with a video data list VDL via the PC/MT air interface PC/MT-LSS to the MT processor MT-P. In the MT processor MT-P the video data list VDL is buffered in the MT storage unit MT-S and output to the display screen AV of the user interface BSS, where the video data list VDL is displayed. A control command "nth video from video list to be transmitted to assigned I/O mobile box for output on television" STK is then transmitted from the keypad  
15 TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P then sends a prompt message "nth video from video list to be transmitted to assigned I/O mobile box for output on television" AFFN via the PC/MT air interface PC/MT-LSS to the PC processor PC-P. After the prompt message AFFM has been transmitted, the PC processor PC-P sends a prompt message "Video output on television" AFM via the PC/MB air interface PC/MB-LSS  
20 to the MB processor MB-P, whereupon the MB processor MB-P transmits an information message "Video output on television" INM via the data interface DSS to the FA processor FA-P. When this information message INM has been sent, the MB processor MB-P sends a response message "Ready for video output" AWN via the PC/MB air interface PC/MB-LSS to the PC processor PC-P.

25 In a subsequent state FZ1 of the message sequence chart applicable to the units and components, the data is transmitted in portions as a function of the quantity of data to be transmitted and the transmission rate of the air interface. To this end, the PC processor PC-P reads a first portion of the nth video data Pl-n-VD from the PC storage unit PC-S. After the



SUBSTITUTE SPECIFICATION - MARKED

34

reading process for this first portion of the nth video data P1-n-VD, the PC processor PC-P transmits this first portion of the nth video data P1 -n-VD via the PC/MB air interface PC/MB-LSS to the MB processor MB-P, which transmits it to the MB storage unit MB-S for buffering and then forwards it to the FA processor FA-P via the data interface DSS, to be  
5 output to the FA screen FA-B of the television FA.

In a subsequent state FZ2 of the message sequence chart applicable to all units and components, the playing of the video film on the television FA is controlled by the user input of check commands on the user interface BSS of the mobile element. Such commands are for example, forward and back, pause, stop, continue, etc. To this end the MB processor MB-P  
10 sends a request message "Next video data" AFM via the PC/MB air interface MC/MB-LSS to the PC processor PC-P. As a result of this request message AFM the PC processor PC-P reads a second portion of the nth video data P2-n-VD from the PC storage unit PC-S. After the reading process for this second portion of the nth video data P2-n-VD, the second portion of the nth video data P2-n-VD is transmitted from the PC processor PC-P via the PC/MB air  
15 interface PC/MB-LSS to the MB processor MB-P, which transfers it to the MB storage unit MB-S for buffering and then forwards it to the FA processor FA-P via the data interface DSS, to be output to the FA screen FA-B of the television FA.

In a subsequent state FZ3 of the message sequence chart applicable to all units and components, the playing of the video film on the television FA is controlled by the user input  
20 check commands on the user interface BSS of the mobile element. Such commands are for example, forward and back, pause, stop, continue, etc. To this end the MB processor MB-P sends a request message "Next video data" AFM via the PC/MB air interface MC/MB-LSS to the PC processor PC-P. As a result of this request message AFM the PC processor PC-P reads an mth portion of the nth video data Pm-n-VD from the PC storage unit PC-S. After the  
25 reading process for this mth portion of the nth video data Pm-n-VD, the mth portion of the nth video data Pm-n-VD is transmitted from the PC processor PC-P via the PC/MB air interface PC/MB-LSS to the MB processor MB-P, which transfers it to the MB storage unit

SUBSTITUTE SPECIFICATION - MARKED

35

MB-S for buffering and then forwards it to the FA processor FA-P via the data interface DSS, to be output to the FA screen FA-B of the television FA.

In a subsequent state FZ4 of the message sequence chart applicable to all units and components, the playing of the video film on the television FA is controlled by the user input  
5 check commands on the user interface BSS of the mobile element. Such commands are for example, forward and back, pause, stop, continue, etc. To this end the MB processor MB-P sends a request message "Next video data" AFM via the PC/MB air interface MC/MB-LSS to the PC processor PC-P. As a result of this request message AFM, the PC processor PC-P transmits a response message "End of transmission" AWM via the PC/MB air interface  
10 PC/MB-LSS to the MB processor MB-P. The MB processor MB-P then sends an information message "Video output terminated" to the FA processor FA-P via the data interface DSS.

Figures 9a to 9d show a sixth message sequence chart according to a sixth smart home scenario, in which the user of the third mobile element MT3 of the telecommunication systems TKS1, TKS2, TKS3 shown in figures 1 to 3, configured as a telecommunication  
15 handset TKHA, outputs an MP3 file, (which is stored for example on the personal computer PC), to the HIFI unit HA. The message sequence required for this operates according to figures 9a to 9d between the ~~third~~second mobile element MT[[3]]2, the personal computer PC with the integrated I/O mobile box card MBK connected to the ~~third~~second mobile element MT[[3]]2 directly via the air interface LSS (point to point connection) or indirectly  
20 via the base station BS, the I/O mobile box MB connected to the personal computer PC via the air interface LSS and the HIFI unit HA connected to the I/O mobile box MB via the circuit connection CINCH, S/PDIF.

The units or components taken into account to represent the message sequence are

(i) for the mobile element MT[[3]]2 a user interface BSS, having a keypad TA and a  
25 display device AV configured as a display screen for example, an MT storage unit MT-S, a central control unit MT-P configured as an MT processor and a shared PC/MT air interface

SUBSTITUTE SPECIFICATION - MARKED

36

PC/MT-LSS operating between the mobile element MT[[3]]2 and the personal computer PC with the integrated I/O mobile box card MBK, which are connected together in the manner shown, and

(ii) for the personal computer PC with the integrated I/O mobile box card MBK the  
5 PC/MT air interface PC/MT-LSS shared with the mobile element MT[[3,]]2, a central control unit MT-P configured as an MT processor, a PC storage unit PC-S and a shared PC/MB air interface PC/MB-LSS operating between the personal computer PC with the integrated I/O mobile box card MBK and the I/O mobile box MB, which are connected together in the manner shown,

10 (iii) for the I/O mobile box MB the PC/MB air interface PC/MB-LSS shared with the personal computer PC with the integrated I/O mobile box card MBK, a central control unit MB-P configured as an MB processor, an MB storage unit MB-S and a shared data interface DSS operating between the I/O mobile box MB and the television FA, which are connected together in the manner shown, and

15 (iv) for the HIFI unit HA the data interface DSS shared with the I/O mobile box MB, a central control unit HA-P configured as an HA processor and an I/O converter E/A-W, which are connected together in the manner shown.

In an optional preliminary state VZ of the message sequence chart applicable to all units and components, both the personal computer PC and the HIFI unit HA can be in  
20 standby mode and be woken up and started up from this state by the mobile element MT[[3]]2 according to the wake-up procedure described in figure 4. In a subsequent initial state AZ of the message sequence chart applicable to all units and components, the MP3 file stored in the personal computer PC is output on the HIFI unit HA. To this end a control command "MP3 list" STK is transmitted from the keypad TA of the user interface BSS by the  
25 MT processor MT-P. The MT processor MT-P transmits a request message "MP3 list" AFM via the PC/MT air interface PC/MT-LSS to the PC processor PC-P. As a result of this request

SUBSTITUTE SPECIFICATION - MARKED

37

message AFM the PC processor PC-P reads all the MP3 data from the PC storage unit PC-S. After this reading process the PC processor PC-P sends a response message AWM with an MP3 data list MP3-DL via the PC/MT air interface PC/MT-LSS to the MT processor MT-P. In the MT processor MT-P the MP3 data list MP3-DL is buffered in the MT storage unit MT-S and output to the display screen AV of the user interface BSS, where the MP3 data list MP3-DL is displayed. A control command "nth MP3 file from MP3 list to be transmitted to assigned I/O mobile box for output on HIFI unit" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P then sends a prompt message "nth MP3 file from MP3 list to be transmitted to assigned I/O mobile box for output on HIFI unit" AFFN via the PC/MT air interface PC/MT-LSS to the PC processor PC-P. After the prompt message AFFM has been transmitted, the PC processor PC-P sends a prompt message "MP3 output on HIFI unit" AFM via the PC/MB air interface PC/MB-LSS to the MB processor MB-P, whereupon the MB processor MB-P transmits an information message "MP3 output on HIFI unit" INM via the data interface DSS to the HA processor HA-P. When this information message INM has been sent, the MB processor MB-P sends a response message "Ready for MP3 output" AWN via the PC/MB air interface PC/MB-LSS to the PC processor PC-P.

In state FZl of the message sequence chart applicable to the units and components "PC processor and PC storage unit", the data is transmitted in portions as a function of the quantity of data to be transmitted and the transmission rate of the air interface. To this end the PC processor PC-P reads a first portion of the nth MP3 data P1-n-MP3-D from the PC storage unit PC-S. After the reading process for this first portion of the nth MP3 data P1-n-MP3-D, the PC processor PC-P transmits the first portion of the nth MP3 data PI-n-MP3-D via the PC/MB air interface PC/MB-LSS to the MB processor MB-P, which transmits it to the MB storage unit MB-S for buffering and then forwards it to the HA processor HFA-P via the data interface DSS, to be output to the I/O converter E/A-W of the HIFI unit HA.

SUBSTITUTE SPECIFICATION - MARKED

38

In a subsequent state FZ2 of the message sequence chart applicable to all units and components, the playing of the MP3 file on the HIFI unit HA is controlled by the user input of check commands on the user interface BSS of the mobile element. Such commands are for example, forward and back, pause, stop, continue, etc. To this end the MB processor MB-P  
5 sends a request message "Next MP3 data" AFM via the PC/MB air interface MC/MB-LSS to the PC processor PC-P. As a result of this request message ATM the PC processor PC-P reads a second portion of the nth MP3 data P2-n-MP3-D from the PC storage unit PC-S. After the reading process for this second portion of the nth MP3 data P2-n-MP3-D, the second portion of the nth MP3 data P2-n-MP3-D is transmitted from the PC processor PC-P  
10 via the PC/MB air interface PC/MB-LSS to the MB processor MB-P, which transfers it to the MB storage unit MB-S for buffering and then forwards it to the HA processor HA-P via the data interface DSS, to be output to the YO converter E/A-W of the HIFI unit HA.

In a subsequent state FZ3 of the message sequence chart applicable to all units and components, the playing of the MP3 file on the HIFI unit HA is controlled by the user input  
15 of check commands on the user interface BSS of the mobile element. Such commands are for example, forward and back, pause, stop, continue, etc. To this end the MB processor MB-P sends a request message "Next MP3 data" AFM via the PC/MB air interface MC/MB-LSS to the PC processor PC-P. As a result of this request message AFM the PC processor PC-P reads an mth portion of the nth MP3 data Pm-n-MP3-D from the PC storage unit PC-S. After  
20 the reading process for this mth portion of the nth MP3 data Pm-n-MP3-D, the mth portion of the nth MP3 data Pm-n-MP3-D is transmitted from the PC processor PC-P via the PC/MB air interface PC/MB-LSS to the MB processor MB-P, which transfers it to the NO storage unit MB-S for buffering and then forwards it to the HA processor HA-P via the data interface DSS, to be output to the VO converter E/A-W of the HIFI unit HA.

25 In a subsequent state FZ4 of the message sequence chart applicable to all units and components, the playing of the MP3 file on the HIFI unit HA is controlled by the user input of check commands on the user interface BSS of the mobile element. Such commands are for



SUBSTITUTE SPECIFICATION - MARKED

39

example, forward and back, pause, stop, continue, etc. To this end the MB processor MB-P sends a request message "Next MP3 data" AFM via the PC/MB air interface MC/MB-LSS to the PC processor PC-P. As a result of this request message AFM the PC processor PC-P transmits a response message "End of transmission" AWM via the PC/MB air interface  
5 PC/MB-LSS to the MB processor MB-P. The MB processor MB-P then sends an information message "MP3 output terminated" to the HA processor HA-P via the data interface DSS.

Figures 10a to 10c show a seventh message sequence chart according to a seventh smart home scenario, in which the user of the third mobile element MT3 of the telecommunication systems TKS1, TKS2, TKS3 shown in figures 1 to 3 configured as a  
10 telecommunication handset TKHA is informed by the mobile element MT[[3]]2 of the start of a television program and its interruption by advertising blocks. The message sequence required for this operates according to figures 10a to 10c between the ~~third~~second mobile element MT[[3]]2 and the set-top box STB connected to this directly via the air interface LSS (point to point connection) or indirectly via the base station BS, with the television FA  
15 connected thereto and the connection to the DVB-T/S/T network DVBN.

The units or components taken into account to represent the message sequence are

(i) for the mobile element MT[[3]]2 a user interface BSS, having an I/O converter E/A-W, a keypad TA and a display device AV configured as a display screen for example, an MT storage unit MT-S, a central control unit MT-P configured as an MT processor and a  
20 shared MT/STB air interface MT/STB-LSS operating between the mobile element MT[[3]]2 and the set-top box STB, which are connected together in the manner shown, and

(ii) for the set-top box STB the MT/STB air interface MT/STB-LSS shared with the mobile element MT[[3]]2, a central control unit STB-P configured as an STB processor, an AS/DS interface AS/DS-SS with a connection to the television FA and a DVB interface  
25 DVB-SS with the connection to the DVB-T/S/T network DVBN, which are connected together in the manner shown.

SUBSTITUTE SPECIFICATION - MARKED

40

In a first initial state AZ of the message sequence chart applicable to all units and components, the mobile element MT3 supplies a reminder of the start of a specific television program. To this end a control command "Television program on channel X on day Y" STK is transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. To  
5 set up an internal communication connection, the MT processor MT-P transmits a set-up message "Internal communication connection" AUM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P. The STB processor STB-P then sends a confirmation message BM via the MT/STB air interface MT/STB-LSS back to the MT processor MT-P. The MT processor MT-P then transmits a request message "Television program on channel X  
10 on day Y" AFM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P. As a result of this incoming request message AFM a "Video text or Electronic Program Guide (EPG)" evaluation AW takes place in the STB processor STB-P, during which video text or EPG signal information VT/EPG-SI (Electronic Program Guide) received via the DVB interface DVB-SS from the DVB-T/S/C network DVBN is evaluated. After the end of this  
15 evaluation AW by the STB processor STB-P, said STB processor STB-P sends a response message AWM with program data PD via the MT/STB air interface MT/STB-LSS to the MT processor MT-P. The MT processor MT-P then outputs the received program data PD to the display screen AV of the user interface BSS, where it is displayed. A control command "Reminder of the start of TV program Z (e.g. favorite sports program)" STK is then sent from  
20 the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P then transmits a request message "Reminder of start of TV program Z" AFM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P. As a result of this received request message AFM, the STB processor STB-P together with the DVB interface DVB-SS monitors "Start of TV program Z" ÜW. After the start of monitoring ÜW, the STB processor  
25 STB-P sends a response message "Reminder request received" AWM via the MT/STB air interface MT/STB-LSS to the MT processor MT-P. As a result of this response message AWM, to cancel the internal communication connection that has been set up, the MT processor MT-P then transmits a cancellation message "Internal communication connection" ABM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P, which the

SUBSTITUTE SPECIFICATION - MARKED

41

latter responds to in the reverse direction by the same route with a further confirmation message DM, as a result of which the connection is canceled.

After this, as a result of the monitoring ÜW, the STB processor STB-P establishes "Start of TV program" FST. To set up an internal communication connection, the STB processor STB-P then transmits a set-up message "Internal communication connection" AUM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P. The MT processor MT-P then sends a confirmation message BM via the MT/STB air interface MT/STB-LSS back to the STB processor STB-P. As a result of this received confirmation message BM, a reminder message "Start of TV program Z" is transmitted from the STB processor STB-P via the MT/STB air interface MT/STB-LSS to the MT processor MT-P, whereupon the MT processor MT-P outputs a first display information item "Start of TV program Z as a text alert (e.g. favorite sports program is starting)" All to the display screen AV of the user interface BSS and/or a second display information item "Alert tone/melody or audio signal for TV program Z (e.g. trailer for favorite sports program)" AI2 to the I/O converter E/A-W of the user interface BSS. The respective display information items AI1, AI2 are then output on the display screen AV and/or to the I/O converter E/A-W. A control command "Reminder message received" STK is then sent from the keypad TA of the user interface BSS to the MT processor MT-P. After receiving the control command STG, to cancel the internal communication connection that has been set up, the MT processor MT-P transmits a cancellation message "Internal communication connection" ABM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P, to which the latter responds in the reverse direction by the same route with a further confirmation message, as a result of which the connection is canceled.

In a subsequent state FZ of the message sequence chart applicable to all units and components, the mobile element MT[[3]]2 supplies a reminder of the continuation of the TV program Z after it has been interrupted by an advertising block, said reminder being output after the end of said advertising block. To this end a control command "Reminder of

SUBSTITUTE SPECIFICATION - MARKED

42

continuation of TV program Z" STK is transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. To set up an internal communication connection, the MT processor MT-P transmits a set-up message "Internal communication connection" AUM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P. The STB processor  
5 STB-P then sends a confirmation message BM via the MT/STB air interface MT/STB-LSS back to the MT processor MT-P. The MT processor MT-P then sends a request message "Reminder of continuation of TV program Z" AFM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P. As a result of this received request message AFM, the STB processor STB-P together with the DVB interface DVB-SS monitors "End of advertising  
10 block" ÜW. After the start of monitoring ÜW, the STB processor STB-P sends a response message "Reminder request received" AWM via the MT/STB air interface MT/STB-LSS to the MT processor MT-P. As a result of this response message AWM, to cancel the internal communication connection that has been set up, the MT processor MT-P then transmits a cancellation message "Internal communication connection" ABM via the MT/STB air  
15 interface MT/STB-LSS to the STB processor STB-P, which the latter responds to in the reverse direction by the same route with a further confirmation message BM, as a result of which the connection is canceled.

After this, as a result of the monitoring ÜW, the STB processor STB-P establishes "End of advertising block" FST. To set up an internal communication connection, the STB  
20 processor STB-P then transmits a set-up message "Internal communication connection" AUM via the MT/STB air interface MT/STB-LSS to the MT processor MT-P. The MT processor MT-P then sends a confirmation message via the MT/STB air interface MT/STB-LSS back to the STB processor STB-P. As a result of this received confirmation message BM, the STB processor STB-P transmits a reminder message "End of advertising block" EM via the  
25 MT/STB air interface MT/STB-LSS to the MT processor MT-P, whereupon the MT processor MT-P outputs a first display information item "Continuation of TV program Z as text alert (e.g. favorite sports program starting again)" All to the display screen AV of the user interface BSS and/or a second display information item "Alert tone/melody or audio



SUBSTITUTE SPECIFICATION - MARKED

43

signal for TV program Z (voice of presenter of favorite sports program,)" AI2 to the I/O converter E/A-W of the user interface BSS. The respective display information item AI1, AI2 is then output on the display screen AV and/or to the I/O converter E/A-W. A control command "Reminder message received" STK is then sent from the keypad TA of the user interface BSS to the MT processor MT-P. After receiving the control command STG, to cancel the internal communication connection that has been set up, the MT processor MT-P transmits a cancellation message "Internal communication connection" ABM via the MT/STB air interface MT/STB-LSS to the STB processor STB-P, to which the latter responds in the reverse direction by the same route with a further confirmation message, as a result of which the connection is canceled.

Figures 11a to 11c show an eighth message sequence chart according to an eighth smart home scenario, in which the user of the **thirdsecond** mobile element MT[[3]]2 of the telecommunication systems TKS1, TKS2, TKS3 shown in figures 1 to 3 configured as a telecommunication handset TKHA uses said mobile element MT[[3]]2 to take part in televoting. The message sequence required for this operates according to figures 11a to 11c between the **thirdsecond** mobile element MT[[3]]2, the set-top box with the connection to the DVB-T/S/T network DVBN connected to the **thirdsecond** mobile element MT[[3]]2, the television FA connected to the set-top box and the base station BS connected to the **thirdsecond** mobile element MT[[3]]2 and the set-top box STB via the air interface LSS.

The units or components taken into account to represent the message sequence are

(i) for the mobile element MT[[3]]2 a user interface BSS, having a keypad TA and a display device AV configured as a display screen for example, an MT storage unit MT-S, a central control unit MT-P configured as an MT processor and a shared MT/BS/STB air interface MT/SB/STB-LSS operating between the mobile element MT[[3]]2 as well as the set-top box STB and the base station BS, which are connected together in the manner shown,



SUBSTITUTE SPECIFICATION - MARKED

44

(ii) for the base station BS the MT/BS/STB air interface MT/SB/STB-LSS shared with the mobile element MT[[3]]2 and the set-top box STB as well as a shared function block comprising a line and network connection LNA, a central control unit BS-P configured as a BS processor and a BS storage unit BS-S, which are connected together in the manner shown

5 (iii) for the set-top box STB the MT/BS/STB air interface MT/BS/STB-LSS shared with the mobile element MT[[3]]2 and the base station BS, a central control unit STB-P configured as an STB processor, a shared AS/DS interface AS/DS-SS operating between the set-top box STB and the television FA as well as a DVB interface DVB-SS with the connection to the DVB-T/S/T network DVBN, which are connected together in the manner  
10 shown, and

(iv) for the television FA the AS/DS interface AS/DS-SS shared with the set-top box STB, a central control unit FA-P configured as an FA processor and an FA screen FA-B, which are connected together in the manner shown.

In an initial state AZ of the message sequence chart applicable to all units and  
15 components, the mobile element MT[[3]]2 is used for televoting. To this end the STB processor STB-P receives a DVB signal "Televoting information" DVB-SI via the DVB interface DVB-SS from the DVB-T/S/C network DVBN. The STB processor STB-P then transmits a display information item "Televoting screen keys" via the AS/DS interface AS/DS-SS, the FA processor FA-P, to the FA screen FA-B and, to set up an internal  
20 communication connection, transmits a set-up message "Internal communication connection" AUM via the MT/BS/STB air interface MT/BS/STB-LSS to the MT processor MT-P. The MT processor MT-P then sends a confirmation message BM via the MT/BS/STB air interface MT/BS/STB-LSS back to the STB processor STB-P. As a result of this confirmation message BM the STB processor transmits a prompt message "Display televoting information" AFFM  
25 to the MT processor MT-P via the MT/BS/STB air interface MT/BS/STB-LSS together with a televoting information item TV 1. After receiving the prompt message AFFM together with the televoting information TV 1, the MT processor MT-P sends a display information item

SUBSTITUTE SPECIFICATION - MARKED

45

"Televoting display keys" to the display screen AV of the user interface BSS, where the televoting display keys are displayed. The MT processor MT-P also sends a confirmation message for the prompt message AFFM received via the MT/BS/STB air interface MT/BS/STB-LSS to the STB processor STB-P. A control command "Televoting decision  
5 made" STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. The MT processor MT-P then transmits a transmission message "Televoting decision data" UM together with televoting decision data WED to the STB processor STB-P. As a result of this transmission message UM, the STB processor STB-P transmits a display information item "Please confirm televoting decision" AI via the AS/DS interface AS/DS-SS  
10 and the FA processor FA-P to the FA screen FA-B and a request message "Confirmation of televoting decision" AFM via the MT/BS/STB air interface MT/BS/STB-LSS to the MT processor MT-P. The MT processor MT-P then outputs a display information item "Please confirm televoting decision" to the display screen AV of the user interface BSS, where said information item is displayed. A control command "Confirmation of televoting decision"  
15 STK is then transmitted from the keypad TA of the user interface BSS to the MT processor MT-P. On receipt of the control command STK the MT processor MT-P sends a response message "Confirmation data" AWM together with confirmation data BSD via the MT/BS/STB air interface MT/BS/STB-LSS to the STB processor STB-P, which sends the received confirmation data BSD via the AS/DS interface AS/DS-SS and the FA processor  
20 FA-P to the FA screen FA-B. To set up an external communication connection, the STB processor STB-P then sends a set-up message "External communication connection" AUM via the MT/BS/STB air interface MT/BS/STB-LSS to the base station BS or the function block made up of the line and network connection LNA, the BS processor BS-P and the BS storage unit BS-S. The base station BS or this function block then sends a confirmation  
25 message BM via the MT/BS/STB air interface MT/BS/STB-LSS back to the STB processor STB-P. As a result of this confirmation message BM the STB processor STB-P transmits a transmission message "Televoting decision data" together with the televoting decision data WED via the MT/BS/STB air interface MT/BS/STB-LSS to the base station BS or the function block, whereupon said base station BS or function block sends a further

SUBSTITUTE SPECIFICATION - MARKED

46

confirmation message in the reverse direction by the same route to the STB processor STB-P. As a result of this confirmation message BM, to cancel the external communication connection that has been set up, the STB processor STB-P transmits a cancellation message "External communication connection" ABM via the MT/BS/STB air interface MT/BS/STB-LSS to the base station BS or the function block, which said base station BS or function block responds to in the reverse direction by the same route with a further confirmation message BM, as a result of which the connection is canceled. The STB processor STB-B then transmits an alert message "Televoting decision data transmitted" HWM via the MT/BS/STB air interface MT/BS/STB-LSS to the MT processor MT-P, whereupon said MT processor MT-P transmits a display information item "Televoting decision data was transmitted" to the display screen AV of the user interface BSS, where said information is displayed. After transmitting the alert message HWM, to cancel the internal communication connection that has been set up, the STB processor STB-P sends a cancellation message "Internal communication connection" ABM via the MT/BS/STB air interface MT/BS/STB-LSS to the MT processor MT-P, which the latter responds to in the reverse direction by the same route with a further confirmation message, as a result of which the connection is canceled.

It should be understood that the various changes and modifications to the presently preferred embodiments described herein will be apparent to those skilled in the art. For example, dynamic frequency selections may be used as a filter. Furthermore, the disclosed method may also be used for establishing connections to a broadcast channel. Such changes and modifications can be made without departing from the spirit and scope of the present disclosure and without diminishing its intended advantages. It is therefore intended that such changes and modifications be covered by the appended claims.

SUBSTITUTE SPECIFICATION - MARKED

47

**ABSTRACT**

In order to achieve simple, user-friendly "smart home" scenarios in a telecommunications system in the context of the transmission of textual, audio, video and/or control data between a data source and a data sink, a mobile element of the telecommunications system generates control commands and transmits the latter in a target manner in message traffic between the units that form part of the wireless communication or telecommunication process via the air interface. The mobile element is preferably configured as a cordless telephone handset or a mobile telephone. Textual, audio, video and/or control data that has been stored in the data source is detected, issued, released or externally transferred to a data sink or issued to a data source with the aid of the control commands.